p0115[3] (2000.00 µs)

ZSW sequence ctrl r0899

	Bit No.	Status word sequence control infeed		
[8932] From sequence control	0	**1 = Ready to power-up**	r0899.0	
[8932] From sequence control	1	**1 = Ready to operate**	r0899.1	
[8932] From sequence control	2	**1 = Operation enabled**	r0899.2	
	3	**Reserved**		
[8932] From sequence control	4	**1 = No OFF2 active**	r0899.4	
	5	**Reserved**		
[8932] From sequence control	6	**1 = Power-on inhibit**	r0899.6	
	7	**Reserved**		
	8	**Reserved**		
Bit 9 = 1 --> Ready to exchange process data	9	**1 = Control requested** <1>	r0899.9	
	10	**Reserved**		
[8950] From power unit	11	**1 = Pre-charging completed**	r0899.11	[8964.5]
[8934.4] From line contactor control	12	**1 = Line contactor closed**	r0899.12	
	13	**Reserved**		
	14	**Reserved**		
	15	**Reserved**		

<1> The master system requests process data.