




GENERAL ELECTRIC		TYPE AK LOW-VOLTAGE POWER CIRCUIT BREAKER		GES-6020	
POWER SENSOR† SOLID-STATE OVERCURRENT-TRIP DEVICE					
Transformer Taps (Amperes)		Long-time-delay and Instantaneous Time-current Curves		Adjustments	
AK-15 & -25	45, 70, 90, 125, 175, 225	(Curves apply at 60 Hertz and from - 20 C to +55 C ambient)		Long-time-delay Unit: Pickup current settings are 80, 90, 100, 110, 120, & 130% of transformer tap setting. (Settings higher than 100% of the frame size rating do not increase the continuous current rating.) Time-delay bands are Max., Int., & Min. Instantaneous Unit: Pickup current settings are 4x, 5x, 6x, 8x, 10x, and 12x of transformer tap setting.	
AK-25 & -50	200, 300, 400, 500, 600				
AK-50	600, 800, 1200, 1600				
AK-75	1500, 2000, 2500, 3000				
AK-100	2000, 2500, 3000, 4000				