

TYPE LF72H HIGH VOLTAGE CONTACTORS
MAGNET CLOSED
7200 VOLT-200 AMPERE-100-400 AMPERE BLOWOUT

S#2078A72G02
S#2078A72G04
S#2078A72G06
S#2078A72G08
S#2078A72G32
S#2078A72G33

S#2078A72G01
S#2078A72G03
S#2078A72G05
S#2078A72G07
S#2078A72G31
S#2078A72G29

VARIABLE PARTS FOR ABOVE	S#2078A72G												STYLE
	01	02	03	04	05	06	07	08	31	32	29	33	NUMBER
BLOWOUT COIT 100 AMP	-	-	-	-	-	-	3	2	3	2	-	-	6410D66G04
BLOWOUT COIL 200 AMP	-	-	-	-	3	2	-	-	-	-	3	3	6410D66G03
BLOWOUT COIL 300 AMP	-	-	3	2	-	-	-	-	-	-	-	-	6410D66G02
BLOWOUT COIL 400 AMP	3	2	-	-	-	-	-	-	-	-	-	-	6410D66G01
CONTACT SHAFT 3 POLE	1	-	1	-	1	-	1	-	1	-	1	1	2044A51G08
CONTACT SHAFT 2 POLE	-	1	-	1	-	1	-	1	-	1	-	-	2044A51G09
PHASE BARRIER - SHORT	4	3	4	3	4	3	4	3	-	-	-	-	657C767H01
PHASE BARRIER - HIGH	-	-	-	-	-	-	-	-	4	3	4	4	6410D66H01

COMMON PARTS FOR ABOVE

NO ILLUSTRATION AVAILABLE

REF	NAME OF PART	STYLE NUMBER	NUMBER PER UNIT
1	MOVING AND STATIONARY CONTACT	316B948G02	2/POLE
2	MOVING CONTACT SPRING	488A898H01	1/POLE
3	MOVING CONTACT SUPPORT	489B727G01	1/POLE
4	MOVING CONTACT SPRING SUPPORT	657C759H01	1/POLE
5	MOVING CONTACT SHUNT	657C766G01	1/POLE
6	MOVING CONTACT PIVOT SHAFT	484B510H02	1/POLE
7	MOVING CONTACT STOP	484B544H01	1/POLE
8	STATIONARY CONTACT INSULATOR	648J248H02	1/POLE
9	SIDE COVER FOR ABOVE	872D210H04	1/POLE
10	STATIONARY CONTACT SUPPORT	657C760G02	1/POLE
11	BLOWOUT COIL	SEE VARIABLE PARTS	1/POLE
12	BLOWOUT COIL CORE	666C932G01	1/POLE
13	BLOWOUT COIL CORE TUBE	484B450H02	1/POLE

REF NO	NAME OF PART	STYLE NUMBER	NUMBER PER UNIT
14	BLOWOUT COIL POLE PIECE - R.H.	872D211G03	1/POLE
14	BLOWOUT COIL POLE PIECE - L.H.	872D211G04	1/POLE
16	ARC BOX ASSEMBLY (R.H. SIDE REMOVED)	2078A72G16	1/POLE
17	ARC SHIELD	872D200H01	2/POLE
18	ARC SHIELD CLIP	484B511H01	2/POLE
19	GRID STACK	636C347G02	1/POLE
20	LINE ARC HORN	872D216G05	1/POLE
*	INSULATOR FOR ABOVE	872D203H02	1/POLE
21	LOAD ARC HORN	872D216G06	1/POLE
*	INSULATOR FOR ABOVE	872D203H01	1/POLE
22	MUFFLER	872D202G01	1/POLE
23	GRID STACK CLAMP	484B424H01	1/POLE
24	ARC BOX SUPPORT INSULATOR	872D207H01	1/POLE
25	ARC SWITCH JAW	316E932H01	2/POLE
26	ARC SWITCH SPRING	316B934H01	2/POLE
27	ARC SWITCH SUPPORT	316B943H01	2/POLE
*	LINE CONNECTOR	6410D68H02	1/POLE
34	LOAD CONNECTOR	657C773G02	1/POLE
35	LOAD CONNECTOR	657C774H01	1/POLE
36	INSULATION TUBE FOR ABOVE	2078A10H04	1/POLE
38	ARMATURE	657C754H01	1
39	ARMATURE CIAMP	657C752H02	1
40	ARMATURE ADJUSTING LEVER	657C751H01	1
*	CONTACT SHAFT WITH INSULATION	SEE VARIABLE PARTS	1
*	CONTACT SHAFT KEY	316B929H03	1
*	CONTACT SHAFT BEARING	430A762H01	2
41	PHASE BARRIER	SEE VARIABLE PARTS	-
42	MAGNET CORE (CENTER)	484B500H01	1
*	MAGNET CORE (OUTSIDE)	657C764H01	1
43	MAGNET YOKE	657C755H01	1
44	MAGNET POLE FACE	640C443H06	1
*	MAGNET RESIDUAL SHIM	484B501H01	1
45	COIL RETAINING WASHER	484B512G01	1
47	TYPE L-64 ELECTRICAL INTERLOCK	843D943G06	1
*	INSULATOR FOR ABOVE	484B534H01	1
48	FINGER SUPPORT INSULATOR	3419D21H01	1
49	WHEEL	484B506H01	4
50	SHOULDER BOLT	488A871H07	4
51	OPERATING COIL	//	1

* NOT ILLUSTRATED
// WHEN ORDERING SUPPLY IDENTIFICATION STAMPED ON COIL