

Parameter r0053

Act StatWd2

r0053
r0053

	Bit No.	Meaning
	0	reserved
Alarm processing →	1	1 = f_act > p2167 (f_off)
Messages →	2	1 = f_act >= p1080 (f_min)
Alarm processing →	3	1 = Act. current r0027 >= p2170
Messages →	4	1 = f_act > p2155 (f_1)
Messages →	5	1 = f_act <= p2155 (f_1)
Messages →	6	1 = f_act >= setpoint
	7	reserved
	8	reserved
Sequence control 1) →	9	1 = Ramping finished
	10	reserved
	11	reserved
	12	reserved
	13	reserved
	14	reserved
	15	reserved

1) The sequence control is the internal control (software) for realizing the drive status (r0002)