



CONTACT KIT INSTRUCTION


FOR TYPE LF50 400 AMP CONTACTOR (SPECIAL)

This contact kit, style number 2121A14G46, has been designed for contact replacement of the Type LF50 400 Amp Contactor (special). For proper operation, the correct spring, 2 supplied, must be installed in the appropriate device. A selection table is provided for this purpose in this leaflet.

The contents of this kit are as follows:

<u>DESCRIPTION</u>	<u>STYLE</u>	<u>QTY.</u>
--------------------	--------------	-------------


Contact	3168948G01	2
---------	------------	---



Contact Spring (1.90 Long)	488A898H01	1
----------------------------	------------	---



Contact Spring (2.11 Long)	488A898H04	1
----------------------------	------------	---



SPRING SELECTION TABLE

DEVICE DESIGNATION	SPRING	
	488A898H01	488A898H04
LF Contactor SNO 490A813	X	
LF Contactor SNO 490A880	X	
LF Contactor SNO 2121A14G01	X	
LF Contactor SNO 2121A14G10	X	
LF Contactor SNO 2121A14G13	X	
LF Contactor SNO 490A879G01		X
LF Contactor SNO 2121A14G11		X

WESTINGHOUSE ELECTRIC CORP.
GENERAL CONTROL DIVISION
ASHEVILLE, N.C., U.S.A. 28813

EFFECTIVE DATE - NOVEMBER 1980